

## Frequency and licensing Information for the G205LD, G205LE and G205LF Microphones.

A license is not required for frequencies between 863.100 MHz and 864.900 MHz. The included free frequencies have been highlighted on the table below and although there are 13 frequencies listed they may not all work together at the same time, you will need to test all frequencies before use. Also listed below are ideal groups of 5, 6 and 8 frequencies that will work together but these frequencies require a license for which you will need to contact your licensing authority (JFMG for the UK, name and address below).

| GP\CH | 0       | 1       | 2       | 3       | 4       | 5       | 6       | 7       | 8       | 9       | A       | B       | C       | D       | E       | F       |
|-------|---------|---------|---------|---------|---------|---------|---------|---------|---------|---------|---------|---------|---------|---------|---------|---------|
| 0     | 851.050 | 851.950 | 852.650 | 853.550 | 854.250 | 855.150 | 855.850 | 856.950 | 857.650 | 858.550 | 859.250 | 860.150 | 861.850 | 863.050 | 863.950 | 864.750 |
| 1     | 851.700 | 851.850 | 854.700 | 856.150 | 861.600 | 862.400 | 859.200 | 858.500 | 861.400 | 852.100 | 857.800 | 857.300 | 860.700 | 861.950 | 851.300 | 857.000 |
| 2     | 852.150 | 853.100 | 857.100 | 861.000 | 852.400 | 859.650 | 863.500 | 857.200 | 853.750 | 854.450 | 861.150 | 854.000 | 862.950 | 857.900 | 863.150 | 858.100 |
| 3     | 852.950 | 853.800 | 851.550 | 863.600 | 857.850 | 863.200 | 856.100 | 859.400 | 861.500 | 853.000 | 860.250 | 861.050 | 863.750 | 862.850 | 863.550 | 855.500 |
| 4     | 851.400 | 858.050 | 858.700 | 859.300 | 861.200 | 851.500 | 859.960 | 860.400 | 857.450 | 858.200 | 855.000 | 855.950 | 854.900 | 863.350 | 856.700 | 857.150 |
| 5     | 852.050 | 855.050 | 856.800 | 853.350 | 854.500 | 856.600 | 854.600 | 862.300 | 860.050 | 851.200 | 858.000 | 862.350 | 856.850 | 853.400 | 851.900 | 856.050 |
| 6     | 853.950 | 856.350 | 858.400 | 860.750 | 862.550 | 858.150 | 856.450 | 862.100 | 854.800 | 858.750 | 862.250 | 858.850 | 859.350 | 861.450 | 860.350 | 854.750 |
| 7     | 854.350 | 856.000 | 859.550 | 862.200 | 863.300 | 860.900 | 857.950 | 859.900 | 858.350 | 862.700 | 861.550 | 859.000 | 851.600 | 859.150 | 851.450 | 852.600 |
| 8     | 853.650 | 862.900 | 859.100 | 863.400 | 854.050 | 861.300 | 851.350 | 860.650 | 862.800 | 859.050 | 852.000 | 852.200 | 853.600 | 862.450 | 861.250 | 857.700 |
| 9     | 851.250 | 854.950 | 860.500 | 855.450 | 857.350 | 861.900 | 858.800 | 862.650 | 853.900 | 854.200 | 856.200 | 856.300 | 854.300 | 859.850 | 852.350 | 856.400 |
| A     | 852.550 | 855.300 | 860.100 | 860.300 | 860.600 | 863.700 | 860.200 | 863.000 | 852.750 | 855.750 | 863.450 | 861.350 | 859.700 | 855.350 | 860.000 | 855.100 |
| B     | 852.300 | 857.750 | 852.800 | 861.800 | 862.750 | 856.750 | 852.500 | 857.050 | 852.250 | 862.500 | 853.500 | 860.800 | 862.050 | 853.700 | 853.200 | 855.650 |
| C     | 853.250 | 854.850 | 859.800 | 863.100 | 863.800 | 851.150 | 859.750 | 858.600 | 855.400 | 860.450 | 863.250 | 856.550 | 855.200 | 851.750 | 859.500 | 854.550 |
| D     | 855.600 | 855.800 | 854.150 | 858.250 | 859.450 | 855.700 | 861.100 | 851.800 | 853.150 | 854.650 | 853.300 | 861.750 | 858.300 | 861.650 | 858.450 | 852.850 |
| E     | 853.450 | 856.650 | 858.900 | 862.000 | 856.250 | 857.600 | 861.700 | 860.850 | 851.650 | 859.600 | 852.700 | 854.400 | 857.550 | 860.550 | 858.650 | 853.850 |
| F     | 857.250 | 857.500 | 852.900 | 856.500 | 855.250 | 855.900 | 856.900 | 855.550 | 851.100 | 852.450 | 863.650 | 860.950 | 853.050 | 862.600 | 858.950 | 854.100 |

### CH 68

851.500  
852.400  
852.900  
853.200  
853.550  
853.750

### CH 69/70

854.900  
863.000

### Free Freq

### Microphone Licensing

For More Information Contact

JFMG Ltd  
33-34 Alfred Place  
London  
WC1E 7DP

Tel: 020 7299 8660

Fax: 020 7299 8661

Out of hours Duty Co-ordinator tel no: 07050 177 335.

Email: [admin@ifmg.co.uk](mailto:admin@ifmg.co.uk)

Web: <http://www.ifmg.co.uk>

### IDEAL GROUPS

| Group of 5 |       | Group of 6 |       | Group of 8 |       |
|------------|-------|------------|-------|------------|-------|
| Freq       | GP/CH | Freq       | GP/CH | Freq       | GP/CH |
| 854.900    | 4/C   | 854.900    | 4/C   | 854.900    | 4/C   |
| 857.950    | 7/6   | 858.200    | 6/9   | 855.900    | F/5   |
| 859.500    | 4/E   | 858.650    | E/E   | 858.200    | 4/9   |
| 860.900    | 7/5   | 860.400    | 4/7   | 858.650    | E/E   |
| 861.550    | 7/A   | 860.500    | 7/5   | 860.400    | 4/7   |
|            |       | 861.550    | 7/A   | 860.900    | 7/5   |
|            |       |            |       | 861.200    | 4/4   |
|            |       |            |       | 861.750    | D/B   |

# UR256-LC 851-865 MHz 10 mW

| Country Code<br>Code de Pays  | Frequency Range.<br>Gamme de Frequences |
|-------------------------------|---|
| A, B, BG, CH, CZ, D, E, EST   | 854-865 MHz*                            |
| FIN, GB, H, HR, I, IRL, IS, L | 854-865 MHz*                            |
| LT, M, NL, P, PL, SLO, TR     | 854-865 MHz*                            |
| DK, F, N, RO, S               | 863-865 MHz*                            |
| CY, GR, LV, SK                | *                                       |
| All Other Countries           | *                                       |

\* Please contact your national frequency authority or agency for the legal frequencies and transmitter power for your country.

Additional frequency information can be found in the userguide

**CE0681!**