


Lemo Connector Wiring for Trantec Beltpack Transmitters



Pin Connections:

Pin 1 Ground

Pin 2 +9v

Pin 3 Audio/+9v

Pin 4 Audio

Wiring for Trantec lapel & headband microphones:

Trantec S259:	Trantec TS33:	Trantec TS44:	Trantec TS55:	Trantec TS912:
Pin 1 Screen	Pin 1 Screen	Pin 1 Screen	Pin 1 Screen	Pin1 Screen
Pin 2 Not connected	Pin 2 Not Connected	Pin 2 Red	Pin 2 Red	Pin 2 Red
Pin 3 White	Pin 3 White and Red	Pin 3 Not Connected	Pin 3 Not Connected	Pin 3 Not Connected
Pin 4 Not Connected	Pin 4 Not Connected	Pin 4 White	Pin 4 White	Pin 4 Yellow

Wiring for some other commonly used lapel microphones:

Sennheiser MKE2 & MKE3:	Sony ECM77:	Sanken COS-11PT:	Beyer MCE5:	Beyer MCE50:
Pin 1 Screen + Blue	Pin 1 Screen + Clear	Pin 1 Screen	Pin 1 Screen	Pin 1 Screen
Pin 2 Not connected	Pin 2 Not Connected	Pin 2 Black	Pin 2 Red	Pin 2 Not Connected
Pin 3 Red	Pin 3 Red	Pin 3 Not Connected	Pin 3 Not Connected	Pin 3 White
Pin 4 Not Connected	Pin 4 Not Connected	Pin 4 White	Pin 4 Blue	Pin 4 Not Connected